




USB 2.0 Fast Ethernet Adapter

The DUB-E100 is a high-speed USB 2.0 10/100Mbps Fast Ethernet adapter for Windows-based desktop and notebook PCs. This adapter is designed to simply plug into any available Universal Serial Bus (USB) port on your computer to connect you to a Fast Ethernet network. Based on USB 2.0, the adapter extends the transfer speed of earlier USB Fast Ethernet adapters to true 10/100Mbps connectivity.

USB 2.0 for True 10/100Mbps Speed

The USB port of the adapter gives you throughput of up to 480Mbps to your computer. That's about 40 times faster than USB 1.1, the earlier USB specification. Now you can take full advantage of your Fast Ethernet network speed to transfer files, send e-mail and upload/download images.

USB Plug-and-Play

As a USB device, this adapter eliminates the need to open your computer's cover to plug a network card into an expansion slot. It also saves your notebook's PC Card slot for other use. Installation and use are further simplified by living up to USB's out-of-the-box installation approach to connecting computer peripherals. You will not have to set IRQ's and other settings for your network connection. configuration is automatic at computer power up, and the

adapter is hot pluggable. The DUB-E100 is equipped with an attached USB 2.0 cable that directly connects to any USB port on your computer. It is backward compatible with USB 1.1, so you can use the adapter with USB 1.1 ports as well (in case no USB 2.0 port is available). The DUB-E100 represents the simplest way to connect your computer to an Ethernet-based network.

Energy Saving Suspend/Resume Function

The DUB-E100 supports USB's energy saving suspend and resume function to minimize power consumption, which is especially useful for laptop/notebook users. Power is provided directly by the USB bus, eliminating the need for an external AC power adapter.

Features

- 10/100Mbps RJ-45 port for connection to Fast Ethernet switch
- USB 2.0 port with attached USB Type A cable for direct connection to PC host
- Ethernet port supports auto-sensing speed, full/half duplex auto-negotiation
- Bus-powered from USB host or USB hub, no external AC power adapter needed
- Embedded 7K x 16-bit SRAM buffer
- Energy saving suspend/resume function
- Runs Windows 98 SE, ME, 2000, XP
- Plug-and-Play installation, hot-swappable

DUB-E100

Technical Specifications

USB 2.0 10/100Mbps Adapter

USB Standards

- USB 1.0, 1.1, 2.0
- OHCI
- EHCI

LAN Standards

- IEEE 802.3 10BASE-T Ethernet
- IEEE 802.3u 100BASE-TX Fast Ethernet
- ANSI/IEEE 802.3 NWay auto-negotiation

Bus-power Supplied

Up to 500mA

Ports

- RJ-45
- 10/100Mbps Fast Ethernet port
- USB 2.0 port directly attached to Type A cable

Diagnostic LEDs

- Power/Link
- Tx/Rx

Physical & Environmental

Operating Voltage

2.5W, 0.5A @ 3.3VDC +/- 10%

Power Consumption

150 mA @ 3.3VDC

Dimensions

81 (L) x 52 (W) x 28 (H) mm

Weight

100 grams

Operating Temperature

0° - 55°C

Storage Temperature

-20° - 70°C

Non-Operating Humidity

0% - 95% non-condensing

Operating Humidity

5% - 95% non-condensing

Emission (EMI)

- FCC Class B
- CE Class B

O.S. Support

Windows 98SE, ME, 2000, XP



Ordering Information

DUB-E100

USB 2.0 10/100Mbps Adapter

D-Link®

Specifications subject to change without prior notice.
D-Link is a registered trademark of D-Link Corporation/D-Link System Inc. All other trademarks belong to their proprietors.

U.S.A.	TEL: 1-949-788-0805	FAX: 1-949-753-7033
Canada	TEL: 1-905-829-5033	FAX: 1-905-829-5095
Europe	TEL: 44-20-8731-5555	FAX: 44-20-8731-5511
U.K.	TEL: 44-20-8731-5555	FAX: 44-20-8731-5511
Germany	TEL: 49-61- 96779900	FAX: 49-61-967799300
France	TEL: 33-1-30238688	FAX: 33-1-30238689
Benelux	TEL: 31-10-204-5740	FAX: 31-10-204-5880
Italy	TEL: 39-02-2900-0676	FAX: 39-02-2900-1723
Iberia	TEL: 34-93-4090770	FAX: 34-93-4910795
Sweden	TEL: 46-(0)8-564-61900	FAX: 46-(0)8-564-61901
Norway	TEL: 47-22-991890	FAX: 47-22-205700
Denmark	TEL: 45-43-969040	FAX: 45-43-424347
Finland	TEL: 358-9-2707-5080	FAX: 358-9-2707-5081
Singapore	TEL: 65-6774-6233	FAX: 65-6774-6322
Australia	TEL: 61-2-8899-1800	FAX: 61-2-8899-1868
Japan	TEL: 81-3-5434-9678	FAX: 81-3-5434-9868
China	TEL: 86-010-8518-2533	FAX: 86-010-8518-2250
India	TEL: 91-22-652-6696	FAX: 91-22-652-8914
Middle East	TEL: 202-6244615	FAX: 202-6244583
South America	TEL: 56-2-232-3185	FAX: 56-2-232-0923
Brasil	TEL: 55-11-3094-2910	FAX: 55-11-3094-2921
South Africa	TEL: 27(0)126652165	FAX: 27(0)126652186
Russia	TEL: 7-095-737-3389	FAX: 7-095-737-3390
Taiwan	TEL: 886-2-2910-2626	FAX: 886-2-2910-1515
D-Link Corp.	TEL: 886-2-2916-1600	FAX: 886-2-2914-6299



RECYCLABLE
Rev. 01 (Dec. 2002)
Printed in Taiwan