

APC® NetShelter®









100-lb Sliding Shelf—AR8123

Overview

The 100-lb Sliding Shelf (AR8123) mounts into an American Power Conversion (APC) NetShelter enclosure. The Sliding Shelf:

- Holds servers and peripherals weighing up to 100 pounds
- Slides forward for access to mounted equipment
- Has adjustable rails (28–40 in.)
- Can be mounted upside down to function as a tray
- Comes with four friction pads for securing your equipment to the shelf
- Is ready for use with the APC Cable Management Arm (AR8129)



Inventory


Item	Qty	Figure
Sliding Shelf	1	
Stationary Rail	2	
Movable Rail	2	
M6 Caged Nut	8	
M6 Plastic Cup Washer	8	
M6 × 16 mm Pan Head Slotted/Phillips Screw	8	
M6 Flanged Nut	4	
Friction Pad	4	

Tools Required

- Screwdriver (flat head)
- Pencil

Mounting Instructions

Step	Action	Figure
1	<p>Choose the location for the Sliding Shelf on the vertical mounting rails of the enclosure. Using a pencil, mark the bottom mounting hole of the chosen U-space on the front and rear vertical mounting rails. (One U-space consists of a notched mounting hole and one hole immediately above and below it.)</p> <p>Caution: Plan to place heavier components towards the bottom of the enclosure.</p>	
2	<p>Install a caged nut in the top and bottom mounting holes of the U-space chosen in Step 1. Repeat for each of the four vertical mounting rails.</p> <p>Caution: Install the caged nuts horizontally, as pictured; that is, the ears of each caged nut should engage the <i>sides</i> of the mounting hole, not the top and bottom.</p>	
3	<p>Assemble the adjustable rails:</p> <p>A. Slide a moveable rail into a slide-stationary rail assembly.</p> <p>B. Using two flanged nuts, fasten the rails loosely enough to allow them to slide.</p> <p>C. Repeat for the other adjustable rail.</p>	



Step	Action	Figure
10	<p>If you are installing the Cable Management Arm (AR8129):</p> <p>Align the plungers on the Cable Management Arm with the holes on either side of the rear of the Sliding Shelf.</p> <p>Fasten the other end of the Cable Management Arm to the vertical mounting rail according to the instructions supplied with AR8129.</p> <p>Note: You will be using the same screws that were used in Step 4 to attach both Sliding Shelf and Cable Management Arm to the enclosure.</p> <p>Caution: Install the Cable Management Arm before placing any equipment on the Sliding Shelf.</p>	